

I'm not a bot



Operating and maintenance manual mattress firm 300 series base

Remove top of shipping carton. Check contents for damage. Be cautious when handling adjustable base due to risk of injury. Two adults are required to move it. Cut zip-ties from electrical power supply and mattress retainer. Carefully lift head section out of carton and place on clean surface. Remove divider from carton and slide foot section next to head section, aligning mounting holes. Use T-Spacers between mounting points, center support brackets, and carriage bolts with nuts. **HAND TIGHTEN.** Route motor cables underneath base frame and connect them. Extend electrical power cord out of head end of base. Screw legs into threaded inserts at corners and center support brackets. Adjust leg height by pushing pin in. Rotate base over onto its legs, remove packaging, and install batteries in remote control. Plug power cord into outlet and test base functions using remote control. Lower base to flat position, install mattress retainer, and place mattress on base. If the adjustable base will not operate, refer to the Troubleshooting section of the owner's manual. To download a copy of the owner's manual or register your adjustable base, visit . 1. Carefully remove the top of the shipping carton and verify its contents for any damage. 2. Cut two zip-ties from the electrical power supply and remove the mattress retainer, setting it aside for now. 3. Lift the base head section out of the shipping carton and place it on a clean surface, then remove the divider from the carton. 4. Carefully slide the head and foot sections together, ensuring they align with the mounting holes at their centers. 5. Place T-Spacers between the mounting points to line up the holes, and insert carriage bolts through the square holes in the center support bracket. 6. Hand tighten all nuts using the provided wrench after installing hardware, then proceed to route cables underneath the base frame. 7. Screw four legs into the threaded inserts at the corners of the base frame and two more into the center support brackets. 8. Adjust leg height by pushing the pin inwards until it reaches 6-10 inches and ensure the base is level on the floor. 9. Rotate the base over onto its legs, remove remaining packaging, and install three batteries in the remote control. 10. Plug the power cord into a power outlet, note that an electrical surge protection device is recommended, and operate the remote control to test the base's functions. 11. Lower the base to its flat position and finally place the mattress retainer at the foot end of the base. ****Compatibility of Mattresses with Adjustable Beds**** Most memory foam, latex, and non-innerspring mattresses are compatible with adjustable beds, but some may not be suited. ****Drawbacks of Adjustable Beds**** ****Higher Costs****: Adjustable beds are generally pricier than traditional ones. ****Increased Noise Levels**** ****Extreme Heaviness**** ****Restricted Movement**** ****Unique Sizing Requirements**** ****Troubleshooting Adjustable Bed Issues**** ****Stopped Working?**: Check for electrical wiring shorts or faulty bed wiring. Try a different outlet or consult warranty for free part replacements. ****Adjustable Beds and Back Pain**** Yes, adjustable beds can exacerbate back pain if: 1. Adjustments don't alleviate pressure on affected back areas. 2. Incorrect usage worsens back conditions. ****Maintenance Needs for Adjustable Beds**** ****Wear and Tear****: Motors and moving parts will eventually require repair or replacement, highlighting the importance of warranties. ****No Oiling Required****: Permanently lubricated motors; avoid applying additional lubricant to prevent malfunctions. ****Noise Reduction Tips**** * Minimize points of contact between the bed frame and supports to decrease vibration noise. ****Connecting Remotes and Adjusting Settings**** ****Mattress Firm 300 Remote Connection****: Wait for rapid flashing (after 5 seconds), then press a button, release, and press again. ****Disabling Child Lock on Ease Remote****: Press and hold FOOT UP and FOOT DOWN buttons for approximately 3 seconds until the backlight flashes twice. ****Understanding Remote Signals**** ****Blinking Remote****: Indicates Child Lock; pressing buttons won't move the base. Disable as described above. ****Sleeping Positions with Adjustable Beds**** ****Side Sleeping in Zero Gravity****: Safe, as it maintains spine alignment and can reduce shoulder stress. ****Leaving the Bed in Upright Position****: Designed for comfort during use; adjust to your preferred level. For longer lifespan, don't keep your mattress elevated when not in use. Place it flat on the ground instead. Important info below: Step 1: Remove carton top and check for any damage to the contents. Setup guide for Adjustable Base: - Legs with pin-adjustable height - Batteries (AAA) - Mattress Retainer - Other items as per model (300 or 600). Note: Two people are required for safe handling and moving of the Adjustable Base.**